

The AV Development Challenge



How to reach full automation as soon as possible?

- Automated vehicles are highly complex systems, as they have to operate safely and reliably in diverse driving environments.
- Testing of autonomous vehicles is a challenging problem which cannot be efficiently handled with conventional approaches.
- Lack of efficient testing can affect time-to-market.
 "14.2 billion miles of testing is needed" Akio
 Toyoda, CEO of Toyota Paris Auto Show 2016


There are many scientific in-depth discussions on the challenges of safety validation for autonomous vehicles, arguing that digitalization and virtual testing should be the main target for both methodological and economic reasons.

Introduction



To assess the safety of automated vehicles various aspects must be taken into account:

- Safe functionality must be ensured through functional safety, as described in ISO 26262. This
 standard focuses on hazards induced by technical failures due to systematic and random faults in
 both hardware and software.
- Additionally, the so-called Safety of the Intended Functionality (SOTIF) must be ensured. <u>SOTIF</u> focuses on an intended function that could induce hazards due to functional insufficiencies, in the absence of technical system failures. SOTIF analysis covers identification of system weaknesses as well as scenarios that lead to a hazardous event.




Restricted © Siemens 2020

Page 3 2020-MM-DD


Introduction (SOTIF) safety of the intended functionality


Objectives of SOTIF:

Decrease area 3 by identifying unknow-unsafe scenarios









3 unknown unsafe scenarios (Area 3)












Restricted © Siemens 2020

Page 4 2020-MM-DD


Siemens Solution for Creation of Unknown-Unsafe Scenarios





Key

- 1 known safe scenarios (Area 1)
- 2 known unsafe scenarios (Area 2)
- 3 unknown unsafe scenarios (Area 3)
- 4 unknown safe scenarios (Area 4)




Restricted © Siemens 2020

Page 5 2020-MM-DD Siemens Digital Industries Software

Phase I: Data collection, Post-Processing & 3D Env. generation

SIEMENS

Ingenuity for life





Phase I: Data collection, Post-Processing & 3D Env. generation How?

SIEMENS Ingenuity for life

3D Environment generation:

- Generation of HD Map from static objects:
 - Sensor fusion
 - Object labeling and road sign detection
- Tracking of dynamic objects:
 - Host vehicle tracking
 - Smooth trajectory
 - Target vehicles tracking
 - Consistent/Stable tracking even if objects disappear from sight of the sensors for few seconds
 - Other road users tracking
- Map matching and localization of the road users trajectories with the generated map






Restricted © Siemens 2020

Page 7 2020-MM-DD Siemens Digital Industries Software

Stable tracking






Restricted © Siemens 2020


Page 8 2020-MM-DD Siemens Digital Industries Software

Stable tracking: causal tracking

Logic track maintenance

- "New-track gate" placed around measurement,
- "Data association gate" around each object, measurements outside gate will be not be assigned.
- A tentative object





Siemens Digital Industries Software

SIEMENS

Ingenuity for life

2020-MM-DD

Stable tracking: causal tracking

SIEMENS

Ingenuity for life


Data association


Gated joint probability data association (JPDA)

 $d_{M,j,i} = \sqrt{(\hat{x}_j - \bar{x}_{m,i})^{\mathsf{T}} \Phi_m^{-1} (\hat{x}_j - \bar{x}_{m,i})}$ Statistical distance:

Weighting:

 $\alpha_{j,i} = \frac{\left(\frac{1}{d_{M_{j,i}}}\right)}{\sum_{i=1}^{n} d_{M_{j,i}}}$ $x_{meas,JPDA,j} = \sum_{i=1}^{n} \left(\alpha_i x_{meas,i}\right)$ Result:





Stable tracking: causal tracking

Kalman estimation

constant acceleration model in discrete time, with sample time τ :

$$x_{k+1} = \begin{bmatrix} 1 & 0 & \tau & 0 & \frac{\tau^2}{2} & 0 \\ 0 & 1 & 0 & \tau & 0 & \frac{\tau^2}{2} \\ 0 & 0 & 1 & 0 & \tau & 0 \\ 0 & 0 & 0 & 1 & 0 & \tau \\ 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 \end{bmatrix} x_k$$


$$A_d$$

Restricted © Siemens 2020

Page 11 2020-MM-DD

SIEMENS

Ingenuity for life



$$y_k = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 \end{bmatrix} x_k \qquad x_k = \begin{bmatrix} p_{x,k} \\ p_{y,k} \\ v_{x,k} \\ v_{y,k} \\ a_{x,k} \\ a_{y,k} \end{bmatrix}$$


 B_d


Stable tracking: merge

SIEMENS Ingenuity for life

Merging forwards and backwards causal tracking result

- use of the similarity gate
 - Possible tracking errors are filtered out, only similar forwards and backwards result are kept
 - Forwards and backwards objects should be within each others gate. If not, the objects are filtered out.
 - · Resulting merged object is the average of the two







Restricted © Siemens 2020


Page 12 2020-MM-DD


Stable tracking: merge


SIEMENS Ingenuity for life














Stable tracking: merge

SIEMENS Ingenuity for life









Restricted © Siemens 2020

Page 14 2020-MM-DD Siemens Digital Industries Software

Stable tracking: tracklet affinity

SIEMENS Ingenuity for life





Restricted © Siemens 2020

Page 15 2020-MM-DD Siemens Digital Industries Software

Stable tracking: tracklet affinity







Time gap filter

Time gap $t_{g,2/1}$ represents the time gap between the **start** of tracklet 2 w.r.t. to the **end** of tracklet 1

$$\begin{bmatrix} 0 & t_{g,2/1} & t_{g,3/1} & \dots & t_{g,j/1} \\ t_{g,1/2} & 0 & t_{g,3/2} & \dots & t_{g,j/2} \\ t_{g,1/3} & t_{g,2/3} & 0 & \dots & t_{g,j/3} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ t_{g,1/j} & t_{g,2/j} & t_{g,3/j} & \dots & 0 \end{bmatrix}$$

 $t_g \leq 0 \rightarrow infeasible to link$





Restricted © Siemens 2020

Page 16 2020-MM-DD


Stable tracking: Occlusion filling methods




Kalman forward/backward merge

Using a merged variant of forward and backward Kalman predicted trajectories to fill an occlusion gives an important issue:

- In some situations, both the forwardsand backwards predictions are faulty. Using a linear merge will therefore not give correct results






Restricted © Siemens 2020

Page 17 2020-MM-DD Siemens Digital Industries Software

Stable tracking: Occlusion filling methods






Optimization approach

Using optimization and drive a virtual vehicle a long the way point

$$J = (x_0 - r_0)^{\mathsf{T}} Q (x_0 - r_0) + (\bar{x} - \bar{r})^{\mathsf{T}} \Omega (\bar{x} - \bar{r}) + \bar{u}^{\mathsf{T}} \Psi \bar{u}$$



Restricted © Siemens 2020


Page 18 2020-MM-DD Siemens Digital Industries Software

Stable tracking: Occlusion filling methods

SIEMENS
Ingenuity for life


The entire state response over a finite time horizon can be computed at once:

$$\bar{x} = \bar{A}_d x_0 + \bar{B}_d \bar{u}$$



...using augmented matrices as such:

$$\begin{bmatrix} x_1 \\ x_2 \\ \vdots \\ x_n \end{bmatrix} = \begin{bmatrix} A_d \\ A_d^2 \\ \vdots \\ A_d^n \end{bmatrix} x_0 + \begin{bmatrix} B_d & 0 & \cdots & 0 \\ A_d B_d & B_d & \cdots & 0 \\ A_d^2 B_d & A_d B_d & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots \\ A_d^n B_d & A_d^{n-1} B_d & \cdots & B_d \end{bmatrix} \begin{bmatrix} u_0 \\ u_1 \\ \vdots \\ u_{n-1} \end{bmatrix}$$



Restricted © Siemens 2020

Page 19


2020-MM-DD

Stable tracking: tracklet affinity

SIEMENS Ingenuity for life

(Constrained) trajectory optimization for all tracklet pairs

 Minimum jerk trajectory penalizing error w.r.t. tracklet states during non-occluded parts





Tracklet pair affinity cost matrix

 Cost function penalizing jerk during the occlusion, and the time gap, thus favouring pairs with low jerk and short occlusions


$$J_{i/j} = \max\left(\left[||\vec{j}_{occl.\,start_{i/j}}||_2\,\dots\,||\vec{j}_{occl.\,end_{i/j}}||_2\right]\right)t_{gap_{i/j}}^2$$

$$\begin{bmatrix} \infty & J_{2/1} & J_{3/1} & \dots & J_{m/1} \\ J_{1/2} & \infty & J_{3/2} & \dots & J_{m/2} \\ J_{1/3} & J_{2/3} & \infty & \dots & J_{m/3} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ J_{1/m} & J_{2/m} & J_{3/m} & \dots & \infty \end{bmatrix}$$

Restricted © Siemens 2020

Stable tracking: tracklet affinity





(Filter most likely tracklet matches

 Minimum cost of all combined tracklet pairs is found using the Hungarian algorithm (with additional no-link cost)

$$\begin{bmatrix} \infty & J_{2/1} & J_{3/1} & \dots & J_{m/1} \\ J_{1/2} & \infty & J_{3/2} & \dots & J_{m/2} \\ J_{1/3} & J_{2/3} & \infty & \dots & J_{m/3} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ J_{1/m} & J_{2/m} & J_{3/m} & \dots & \infty \end{bmatrix}$$

Restricted © Siemens 2020

Data collection, Post-Processing & 3D Env. generation





REAL-LIFE DRIVING
SCENARIOS IN PRESCAN
SIMULATION ENGINE


FORESIGHT ALINC. MAY 2019.

Restricted © Siemens 2020

Page 22 2020-MM-DD Siemens Digital Industries Software

Unknown-Unsafe Scenarios









Phase I:
Data collection,
Post-Processing &
3D Env. generation

Phase II:
Scene selection &
Basic scenario
elements extraction

Phase III: Massive scenario & test case generation Phase IV: Generation of Unknown-Unsafe Scenarios

Restricted © Siemens 2020

Page 23 2020-MM-DD Siemens Digital Industries Software

Unknown-Unsafe Scenarios in Different ODDs











Restricted © Siemens 2020

Page 24 2020-MM-DD Siemens Digital Industries Software



Mohsen Alirezaei, PhD

Fellow Scientist @ RTD department of Siemens

Mohsen.Alirezaei.ext@siemens.com